

CONFIDENTIAL

R-Car V4M AUTOSAR R19-11 MCAL

Appendix

RTM8RC779HCMCL5DA0JCDRE
RTM8RC779HCMCL5QA0JCDRE

Target Device:
R-Car V4M

All information contained in these materials, including products and product specifications, represents information on the product at the time of publication and is subject to change by Renesas Electronics Corp. without notice. Please review the latest information published by Renesas Electronics Corp. through various means, including the Renesas Electronics Corp. website (<http://www.renesas.com>).

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.

"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.

"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.

Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.

7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-1 October 2020)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan

www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:

www.renesas.com/contact/

1. Introduction

This document shall be used as reference by the users for module ROM/RAM usage, module stack size and module API execution time of AUTOSAR R19-11 for Gen4/V4M MCAL.

Modules:

- CAN
- GPT
- DIO
- ETH
- THS
- FLS
- MCU
- PORT
- SPI
- WDG
- CRC
- EMM
- ICCOM
- IIC
- IPMMU
- RFSO

2. Memory Usage and Execution Time

2.1 Module ROM/RAM Usage

Module ROM/RAM usage shows the memory size allocated for each section used in each module.

2.2 Module Stack Size

Module stack size shows the max of stack size used in each module.
The unit of module stack size is Byte(s).

2.3 Module API Execution Time

Module API execution time shows the execution time of each module API.
The unit of module API execution time is microsecond.

3. Measurement Condition

Each module was measured with the following conditions:

- Typical configuration was used as the base configuraion for measurement. For details of configuration file, refer to the each module section.
- The CPU clock frequency used to measure the Execution Time is 1400 MHz for all the APIs.

The list of CDF files used for measurement are as below:

Module	CDF name	Remark
CAN	RCar_CAN_008.arxml	DET ON
	RCar_CAN_009.arxml	DET OFF
	RCar_CAN_001.arxml	DET ON
	RCar_CAN_014.arxml	DET ON
	RCar_CAN_RC_002.arxml	DET ON
GPT	RCar_Gpt_013.arxml	DET ON
	RCar_Gpt_014.arxml	DET OFF
DIO	RCar_Dio_007.arxml	DET ON
	RCar_Dio_008.arxml	DET OFF
ETH	RCar_Eth_011.arxml	DET ON
	RCar_Eth_012.arxml	DET OFF
THS	RCar_Cddths_030.arxml	DET OFF
	RCar_Cddths_031.arxml	DET ON
FLS	RCar_Fls_123.arxml	DET OFF
	RCar_Fls_124.arxml	DET ON
	RCar_Fls_138.arxml	DET OFF
	RCar_Fls_140.arxml	DET ON
MCU	RCar_Mcu_009.arxml	DET ON
	RCar_Mcu_010.arxml	DET OFF
	RCar_Mcu_017.arxml	DET OFF
PORT	RCar_Port_014.arxml	DET OFF
	RCar_Port_019.arxml	DET ON
SPI	RCar_Spi_003.arxml	DET OFF
	RCar_Spi_061.arxml	DET OFF
	RCar_Spi_060.arxml	DET ON
	RCar_Spi_067.arxml	DET ON
WDG	RCAR_Wdg_029.arxml	DET OFF
	RCAR_Wdg_030.arxml	DET ON
CRC	RCar_CddCrc_001.arxml	DET ON
	RCar_CddCrc_003.arxml	DET OFF
EMM	RCar_CddEmm_018.arxml	DET OFF
	RCar_CddEmm_019.arxml	DET ON
ICCOM	RCar_CddIccom_091.arxml	DET OFF
	RCar_CddIccom_092.arxml	DET ON
IIC	RCar_CddIic_143.arxml	DET ON
	RCar_CddIic_144.arxml	DET OFF
	RCar_CddIic_148.arxml	DET ON
IPMMU	RCar_CddIpmmu_041.arxml	DET ON
	RCar_CddIpmmu_040.arxml	DET OFF
RFSO	RCar_Cddrfso_011.arxml	DET ON
	RCar_Cddrfso_012.arxml	DET OFF
	RCar_Cddrfso_025.arxml	DET OFF

Note: All *.arxml files are attached in the release package

4 CAN

4.1 CAN ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_CAN_008.arxml(DET_ON)' and 'RCar_CAN_009.arxml(DET_OFF)' configuration.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CAN_PUBLIC_CODE_ROM	9344	7664
	CAN_PRIVATE_CODE_ROM	6536	6420
	CAN_APPL_CODE_ROM	80	80
	CAN_FAST_CODE_ROM	2812	2812
	CONST_ROM_8BIT	89	89
	CAN_CFG_DBTOC_UNSPECIFIED	436	436
	CAN_CFG_DATA_8BIT	2	2
	CAN_CFG_DATA_UNSPECIFIED	68	68
	Total	19367	17571
RAM	RAM_1BIT	6	6
	RAM_8BIT	2	2
	RAM_32BIT	12	12
	RAM_UNSPECIFIED	48	48
	NOINIT_RAM_1BIT	5	5
	NOINIT_RAM_8BIT	2	2
	NOINIT_RAM_32BIT	12	12
	NOINIT_RAM_UNSPECIFIED	48	48
	Total	135	135
Total	-	19502	17706

4.2 CAN Stack Size

This section provides the max of stack depth for the 'RCar_CAN_008.arxml(DET_ON)' and 'RCar_CAN_009.arxml(DET_OFF)' configuration.

Max of stack depth (Bytes)	800
-----------------------------------	-----

4.3 CAN API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_CAN_001.arxml', 'RCar_CAN_009.arxml', 'RCar_CAN_014.arxml' and 'RCar_CAN_RC_002.arxml' configuration.

API Name	Execution time (us)	Remarks
Can_Init	6.5	-
Can_MainFunction_Write	1.8	-
Can_SetControllerMode_START	8.7	-
Can_SetControllerMode_STOP	8.9	-
Can_SetControllerMode_SLEEP	0.0	-
Can_DisableControllerInterrupts	0.1	-
Can_EnableControllerInterrupts	0.2	-
Can_Write	1.5	-
Can_GetVersionInfo	0.2	-
Can_MainFunction_Read	3.1	-
Can_MainFunction_BusOff	0.9	-
Can_MainFunction_Mode	0.2	-
Can_SetBaudrate	0.4	-
Can_GetControllerMode	0.1	-
Can_GetControllerErrorState	0.5	-
Can_GetControllerTxErrorCounter	0.3	-
Can_GetControllerRxErrorCounter	0.3	-
Can_SelfTestChannel	16.5	-
Can_RAMTest	50181.3	-
Can_SetlcomConfiguration	12.7	-
Can_DelInit	6.1	-
ISR_RX_RXFIFO_MODE	9.8	-
ISR_RX_TXRXFIFO_MODE	10.9	-
ISR_TX_BUFFER_MODE	7.9	-
ISR_TX_TXRXFIFO_MODE	9.3	-
ISR_TX_QUEUE_MODE	8.8	-
ISR_BUSOFF	6.9	-

5 GPT

5.1 GPT ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_Gpt_013.arxml' (DET ON) configuration and 'RCar_Gpt_014.arxml' (DET OFF) configuration.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	GPT_PUBLIC_CODE_ROM	4664	3192
	GPT_PRIVATE_CODE_ROM	1960	1960
	GPT_FAST_CODE_ROM	360	360
	GPT_CFG_DATA_UNSPECIFIED	188	176
	GPT_CFG_DBTOC_UNSPECIFIED	16	16
	Total	7188	5704
RAM	RAM_1BIT	1	1
	GPT_CFG_RAM_UNSPECIFIED	12	12
	VAR_NO_INIT_PTR	12	12
	NOINIT_RAM_8BIT	1	1
	Total	26	26
Total	-	7214	5730

5.2 GPT Stack Size

This section provides the max of stack depth for the 'RCar_Gpt_013.arxml' configuration.

Max of stack depth (Bytes)	224
-----------------------------------	-----

5.3 GPT API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_Gpt_014.arxml' configuration.

API Name	Execution time (us)	Remarks
Gpt_Init	24.5	-
Gpt_DeInit	11.6	-
Gpt_GetTimeElapsed	2.2	-
Gpt_GetTimeRemaining	0.8	-
Gpt_StartTimer	7.0	-
Gpt_StopTimer	1.8	-
Gpt_EnableNotification	0.2	-
Gpt_DisableNotification	0.04	-
Gpt_GetPredefTimerValue	1.0	-
Gpt_GetVersionInfo	0.1	-
Gpt_SetMode	0.9	-
Gpt_DisableWakeup	2.1	-
Gpt_EnableWakeup	0.3	-
Gpt_CheckWakeup	0.3	-
Gpt_HW_Tmu_CbkNotification	0.9	-

6 DIO

6.1 DIO ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_Dio_007.arxml' configuration with DET enabled and 'RCar_Dio_008.arxml' configuration with DET disabled.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	DIO_PUBLIC_CODE_ROM	1036	648
	DIO_PRIVATE_CODE_ROM	524	524
	DIO_CFG_DATA_UNSPECIFIED	100	100
	Total	1660	1272
RAM	-	0	0
Total	-	1660	1272

6.2 DIO Stack Size

This section provides the max of stack depth for the 'RCar_Dio_007.arxml' configuration.

Max of stack depth (Bytes)	128
-----------------------------------	-----

6.3 DIO API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_Dio_008.arxml' configuration.

API Name	Execution time (us)	Remarks
Dio_WriteChannel	3.0	-
Dio_ReadChannel	3.1	-
Dio_WritePort	2.5	-
Dio_ReadPort	3.0	-
Dio_WriteChannelGroup	2.6	-
Dio_ReadChannelGroup	3.1	-
Dio_MaskedWritePort	2.6	-
Dio_FlipChannel	4.4	-
Dio_GetVersionInfo	0.02	-
Dio_ReadChannelOutputValue	0.7	-
Dio_ReadChannelGroupOutputValue	0.7	-

7 ETH

7.1 ETH ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_Eth_011.xml' configuration for DET ON, 'RCar_Eth_012.xml' for DET OFF.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	ETH_PUBLIC_CODE_ROM	7084	3756
	ETH_PRIVATE_CODE_ROM	15048	14936
	ETH_FAST_CODE_ROM	324	324
	CONST_ROM_32BIT	32	32
	ETH_CFG_DBTOC_UNSPECIFIED	8	8
	ETH_CFG_DATA_UNSPECIFIED	660	660
	Total	23156	19716
RAM	RAM_UNSPECIFIED	40	40
	NOINIT_RAM_32BIT	12	12
	NOINIT_RAM_UNSPECIFIED	6048	6048
	RAM_16BIT	72	72
	RAM_32BIT	24	24
	ETH_PORT_RAM_0	101072	101072
	ETH_PORT_RAM_1	101072	101072
	ETH_PORT_RAM_2	101072	101072
	ETH_PORT_DESCRIPTOR_0	1328	1328
	ETH_PORT_DESCRIPTOR_1	1328	1328
	ETH_PORT_DESCRIPTOR_2	1328	1328
	Total	313396	313396
	Total	-	336552

7.2 ETH Stack Size

This section provides the max of stack depth for the 'RCar_Eth_012.xml' configuration.

Max of stack depth (Bytes)	576
-----------------------------------	-----

7.3 ETH API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_Eth_012.xml' configuration.

API Name	Execution time (us)	Remarks
Eth_Init	15.7	-
Eth_SetControllerMode (MODE_ACTIVE)	57.8	-
Eth_SetControllerMode (MODE_DOWN)	4.7	-
Eth_GetControllerMode	0.09	-
Eth_GetPhysAddr	0.09	-
Eth_SetPhysAddr	0.22	-
Eth_UpdatePhysAddrFilter	0.35	-
Eth_WriteMii	41.4	-
Eth_ReadMii	40.5	-
Eth_GetCounterValues	0.91	-
Eth_GetRxStats	2.6	-
Eth_GetTxStats	0.02	-
Eth_GetTxErrorCounterValues	0.09	-
Eth_ProvideTxBuffer	1.1	-
Eth_Transmit	2.3	-
Eth_Receive	3.5	-
Eth_TxConfirmation	2.2	-
Eth_GetVersionInfo	0.3	-
Eth_MainFunction	2.7	-
Eth_GetCurrentTime	1.1	-
Eth_EnableEgressTimeStamp	0.46	-
Eth_GetEgressTimeStamp	1.1	-
Eth_GetIngressTimeStamp	0.76	-
Eth_SetIncrementTimeForGptp	0.02	-
Eth_SetOffsetTimeForGptp	0.03	-
Eth_UpdateStreamFilter	0.46	-
ETH_AVBnDATAISR (Transmit)	2.3	-
ETH_AVBnDATAISR (Receive)	4.0	-

8 CDDTHS

8.1 CDDTHS ROM/RAM Usage

This section provides memory usage details measured using the RCar_Cddths_030.arxml and RCar_Cddths_031.arxml configuration.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CODE_SLOW	3548	2416
	CONFIG_DATA_UNSPECIFIED	32	32
	Total	3580	2448
RAM	VAR_INIT_8	1	0
	VAR_INIT_UNSPECIFIED	4	4
	VAR_NO_INIT_PTR	4	4
	Total	9	8
Total	-	3589	2456

8.2 CDDTHS Stack Size

This section provides max of stack depth measured using the RCar_Cddths_030.arxml and RCar_Cddths_031.arxml configuration.

Max of stack depth (Bytes)	320
-----------------------------------	-----

8.3 CDDTHS API Execution Time

This section provides excution time detail measured using the RCar_Cddths_030.arxml configuration.

API Name	Execution time (us)	Remarks
CddThs_Init	2237.1	-
CddThs_SetThermalInterruptMode	1.7	-
CddThs_ConfigureThermalInterrupt	8.1	-
CddThs_GetCurrentTemperature	3.7	-
CddThs_GetCurrentVoltage	0.9	-
CddThs_SetOperationState	2106.6	-
CddThs_GetOperationState	0.03	-
CddThs_GetVersionInfo	0.02	-
CddThs_DeInit	2111.7	-
CddThs_ClearTemperatureErrorStatus	0.02	-

9 FLS

9.1 FLS ROM/RAM Usage

This section provides memory usage details measured using the: RCar_Fls_123.xml configuration for Serial Flash (DET_OFF), RCar_Fls_124.xml configuration for Serial Flash (DET_ON), RCar_Fls_138.xml configuration for Hyper Flash (DET_OFF), RCar_Fls_140.xml configuration for Hyper Flash (DET_ON).

ROM/RAM for HyperFlash	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CODE_FAST	0	0
	CODE_SLOW	16172	13980
	CONFIG_DATA_UNSPECIFIED	636	636
	Total	16808	14616
RAM	VAR_INIT_UNSPECIFIED	8	8
	VAR_NO_INIT_UNSPECIFIED	76	76
	VAR_NO_INIT_PTR	4	4
	Total	88	88
Total	-	16896	14704

ROM/RAM for SerialFlash	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CODE_FAST	0	0
	CODE_SLOW	18236	15604
	CONFIG_DATA_UNSPECIFIED	928	928
	Total	19164	16532
RAM	VAR_INIT_UNSPECIFIED	8	8
	VAR_NO_INIT_UNSPECIFIED	84	84
	VAR_NO_INIT_PTR	4	4
	Total	96	96
Total	-	19260	16628

9.2 FLS Stack Size

This section provides memory usage details measured using the: RCar_Fls_123.xml configuration for Serial Flash (DET_OFF), RCar_Fls_124.xml configuration for Serial Flash (DET_ON), RCar_Fls_138.xml configuration for Hyper Flash (DET_OFF), RCar_Fls_140.xml configuration for Hyper Flash (DET_ON).

Max of stack depth for HyperFlash (Bytes)	1248
Max of stack depth for Serial Flash (Bytes)	1536

9.3 FLS API Execution Time

This section provides memory usage details measured using the: RCar_Fls_123.xml configuration for Serial Flash (DET_OFF), RCar_Fls_138.xml configuration for Hyper Flash (DET_OFF).

API Name	Execution time (us)		Remarks
	SerialFlash	HyperFlash	
Fls_GetVersionInfo	1.9	0.30	-
Fls_Init	1.8	80.6	-
Fls_Erase	1.8	1.5	-
Fls_MainFunction(Erase)	96.7	918166.7	-
Fls_MainFunction(BlankCheck)	23.6	46.9	-
Fls_MainFunction(Write)	25.5	2221.4	-
Fls_MainFunction(Compare)	1.9	50.0	-
Fls_MainFunction(Read)	0.02	32.5	-
Fls_BlankCheck	0.08	1.3	-
Fls_Write	0.36	1.4	-
Fls_Read	24.9	1.3	-
Fls_SetMode	89.6	0.26	-
Fls_GetStatus	92.7	0.02	-
Fls_GetJobResult	938470.8	0.02	-
Fls_Compare	59.1	1.5	-
Fls_Cancel	2514.8	1.4	-
Fls_SendSpecificConfig(Read)	1.8	26.9	-
Fls_SendSpecificConfig(Write)	1.9	26.6	-
Fls_DDRWritePattern	21.9	0.0	This function is not supported in Hyper Flash
Fls_DDRVerifyPattern	21.1	0.0	This function is not supported in Hyper Flash
Fls_DDRCalibrate	0.29	0.0	This function is not supported in Hyper Flash
Fls_Suspend	1.8	1.4	-
Fls_Resume	1.8	1.3	-

10 MCU

10.1 MCU ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_Mcu_009.arxml' and 'RCar_Mcu_010.arxml' configuration.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	MCU_PUBLIC_CODE_ROM	1200	536
	MCU_PRIVATE_CODE_ROM	3800	3800
	CONFIG_DATA_8	24	24
	CONFIG_DATA_32	1192	1192
	CONST_UNSPECIFIED	128	128
	CONFIG_DBTOC_DATA_UNSPECIFIED	44	44
	CONFIG_DATA_UNSPECIFIED	52	52
	Total	6440	5776
RAM	VAR_INIT_1	4	4
	VAR_NO_INIT_32	12	12
	VAR_NO_INIT_PTR	32	32
	Total	48	48
Total	-	6488	5824

10.2 MCU Stack Size

This section provides the max of stack depth for the 'RCar_Mcu_009.arxml' configuration.

Max of stack depth (Bytes)	192
-----------------------------------	-----

10.3 MCU API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_Mcu_017.arxml' configuration.

API Name	Execution time (us)	Remarks
Mcu_Init	0.3	-
Mcu_InitClock	238.1	-
Mcu_InitRamSection	1.2	-
Mcu_GetPIIStatus	1.2	-
Mcu_DistributePIIClock	86.6	-
Mcu_GetRamState	0.01	-
Mcu_GetResetReason	1.9	-
Mcu_GetResetRawValue	0.1	-
Mcu_GetVersionInfo	0.1	-
Mcu_SetMode	0.2	-
Mcu_PerformReset	0.03	-

11 PORT

11.1 PORT ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_Port_019.xml' configuration with DET enabled and the 'RCar_Port_014.xml' configuration with DET disabled

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	PORT_PUBLIC_CODE_ROM	1304	888
	PORT_PRIVATE_CODE_ROM	5732	5676
	CONFIG_DATA_UNSPECIFIED	1988	1988
	PORT_CFG_DBTOC_UNSPECIFIED	40	40
	Total	9064	8592
RAM	VAR_INIT_1	1	1
	VAR_NO_INIT_32	8	8
	VAR_NO_INIT_PTR	4	4
	Total	13	13
Total	-	9077	8605

11.2 PORT Stack Size

This section provides the max of stack depth for the 'RCar_Port_019.xml' configuration with DET enabled and the 'RCar_Port_014.xml' configuration with DET disabled

Max of stack depth (Bytes)	
	272

11.3 PORT API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_Port_014.xml' configuration.

API Name	Execution time (us)	Remarks
Port_Init	171.4	-
Port_SetPinDirection	5.4	-
Port_GetVersionInfo	0.1	-
Port_SetPinDefaultDirection	5.3	-
Port_SetToDioMode	2.6	-
Port_SetToAlternateMode	0.9	-
Port_RefreshPortDirection	15.0	-
Port_SetPinMode	0.6	-
Port_FUSEMonitoring	1.6	-
Port_UnintendedModuleStopCheck	1.3	-

12 SPI

12.1 SPI ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_Spi_003.xml' (DET OFF) and 'RCar_Spi_060.xml' (DET ON) configurations.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	SPI_PUBLIC_CODE_ROM	4128	2700
	SPI_PRIVATE_CODE_ROM	9588	9588
	CODE_FAST	312	312
	CONST_UNSPECIFIED	48	48
	CONFIG_DBTOC_DATA_UNSPECIFIED	36	36
	CONFIG_DATA_UNSPECIFIED	349	349
	Total	14461	13033
RAM	VAR_INIT_1	1	1
	VAR_NO_INIT_32	272	272
	VAR_NO_INIT_UNSPECIFIED	232	232
	VAR_NO_INIT_PTR	24	24
	Total	529	529
Total	-	14990	13562

12.2 SPI Stack Size

This section provides the max of stack depth for the 'RCar_Spi_003.xml' (DMA OFF / DET OFF), 'RCar_Spi_060.xml' (DMA OFF / DET ON), 'RCar_Spi_061.xml' (DMA ON / DET OFF), 'RCar_Spi_067.xml' (DMA ON / DET ON) configurations.

Max of stack depth (Bytes)	528
-----------------------------------	-----

12.3 SPI API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_Spi_003.xml' for API and 'RCar_Spi_061.xml' for SPI_DMA0_00_ISR configurations.

API Name	Execution time (us)	Remarks
Spi_Init	24.2	-
Spi_DeInit	13.3	-
Spi_WriteB	0.9	-
Spi_AsyncTransmit	126.0	-
Spi_ReadB	0.7	-
Spi_SetupEB	0.1	-
Spi_GetStatus	0.2	-
Spi_GetJobResult	0.0	-
Spi_GetSequenceResult	0.0	-
Spi_GetVersionInfo	0.1	-
Spi_SyncTransmit	22240.7	-
Spi_GetHWUnitStatus	0.1	-
Spi_Cancel	0.8	-
Spi_SetAsyncMode(SPI_INTERRUPT_MODE)	0.1	-
Spi_SetAsyncMode(SPI_POLLING_MODE)	4.8	-
Spi_MainFunction_Handling	1.8	-
Spi_ForceCancel	22044.4	-
SPI_MSIOFn_ISR	68.1	-
SPI_DMAj_nn_ISR	60.0	-

13 WDG

13.1 WDG ROM/RAM Usage

This section provides memory usage details measured using the 'RCAR_Wdg_029.arxml' and 'RCAR_Wdg_030.arxml' configuration.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	WDG_PUBLIC_CODE_ROM	480	164
	WDG_PRIVATE_CODE_ROM	1508	1892
	CODE_FAST	136	136
	CONFIG_DBTOC_DATA_UNSPECIFIED	32	32
	CONST_UNSPECIFIED	12	12
	Total	2168	2236
RAM	VAR_INIT_UNSPECIFIED	4	0
	VAR_NO_INIT_UNSPECIFIED	4	4
	VAR_NO_INIT_PTR	8	8
	VAR_NO_INIT_32	12	12
	Total	28	24
Total	-	2196	2260

13.2 WDG Stack Size

This section provides the max of stack depth for the 'RCAR_Wdg_029.arxml' and 'RCAR_Wdg_030.arxml' configuration.

Max of stack depth (Bytes)	224
-----------------------------------	-----

13.3 WDG API Execution Time

This section provides Execution Time details of the API measured using the 'RCAR_Wdg_029.arxml'

API Name	Execution time (us)	Remarks
Wdg_Init	124.5	-
Wdg_SetMode	0.1	-
Wdg_SetTriggerCondition	119.5	-
Wdg_GetVersionInfo	0.1	-
Wdg_Cbk_GptNotification	0.9	-

14 CDDCRC

14.1 CDDCRC ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_CddCrc_001.arxml' configuration with DET enabled and 'RCar_CddCrc_003.arxml' configuration with DET disabled.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CDDCRC_PRIVATE_CODE_ROM	2192	2192
	CDDCRC_PUBLIC_CODE_ROM	3592	1920
	CODE_FAST	768	768
	CONFIG_DBTOC_DATA_UNSPECIFIED	20	20
	CONFIG_DATA_UNSPECIFIED	804	804
	CONST_UNSPECIFIED	24	24
	Total	7400	5728
RAM	VAR_INIT_8	1	1
	VAR_CLEARED_UNSPECIFIED	192	192
	VAR_NO_INIT_PTR	16	16
	VAR_CLEARED_DESC_UNSPECIFIED	384	384
	Total	593	593
Total	-	7993	6321

14.2 CDDCRC Stack Size

This section provides the max of stack depth for the 'RCar_CddCrc_001.arxml' configuration.

Max of stack depth (Bytes)	256
-----------------------------------	-----

14.3 CDDCRC API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_CddCrc_003.arxml' configuration.

API Name	Execution time (us)	Remarks
CddCrc_GetVersionInfo	0.1	-
CddCrc_Init	5.2	-
CddCrc_Process	4.2	-
CddCrc_SetMode	0.3	-
CddCrc_SetupEB	0.6	-
CddCrc_Write	0.7	-
CddCrc_ReadStatus	0.1	-
CddCrc_Compare	2.4	-
CddCrc_ReadCompareResult	0.3	-
CddCrc_Command	0.8	-
CddCrc_UnintendedModuleStopCheck	2.0	-
CddCrc_Stop	0.8	-
CDDCRC_DMAxx_ISR	0.9	-

15 CDEMM

15.1 CDEMM ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_CddEmm_018.arxml' (DET OFF) and 'RCar_CddEmm_019.arxml' (DET ON) configuration.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CODE_SLOW	4184	3084
	CODE_FAST	6120	6120
	CONFIG_DATA_32	7028	7028
	Total	17332	16232
RAM	VAR_INIT_1	4	4
	VAR_CLEARED_32	1084	1084
	VAR_NO_INIT_PTR	16	16
	Total	1104	1104
Total	-	18436	17336

15.2 CDEMM Stack Size

This section provides the max of stack depth for the 'RCar_CddEmm_019.arxml' configuration.

Max of stack depth (Bytes)	224
-----------------------------------	-----

15.3 CDEMM API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_CddEmm_018.arxml' configuration.

API Name	Execution time (us)	Remarks
CddEmm_GetVersionInfo	0.2	-
CddEmm_Init	34.6	-
CddEmm_SupportPseudoError	0.5	-
CddEmm_SetTarget	0.5	-
CddEmm_SetPseudoErrorSignal	0.5	-
CddEmm_ReadErrorStatus	3.0	-
CddEmm_ClearPseudoErrorSignal	0.2	-
CddEmm_ClearErrorStatus	0.8	-
CddEmm_GetCurrentErrorCountUpValue	5.4	-
CddEmm_SetHoldMaskCounter	0.3	-
CddEmm_SupportControlExternalErrorRequest	0.4	-
CDDEMM_DOMAIN0_ISR	1.2	-
CDDEMM_DOMAIN1_ISR	0.9	-
CDDEMM_DOMAIN2_ISR	0.9	-
CDDEMM_DOMAIN3_ISR	0.9	-
CDDEMM_DOMAIN4_ISR	0.9	-
CDDEMM_DOMAIN5_ISR	0.9	-
CDDEMM_DOMAIN6_ISR	0.9	-
CDDEMM_DOMAIN7_ISR	0.9	-
CDDEMM_DOMAIN8_ISR	0.9	-
CDDEMM_DOMAIN9_ISR	0.9	-
CDDEMM_DOMAIN10_ISR	0.9	-
CDDEMM_DOMAIN11_ISR	0.9	-
CDDEMM_DOMAIN12_ISR	0.9	-
CDDEMM_DOMAIN16_ISR	1.0	-
CDDEMM_DOMAIN17_ISR	0.9	-
CDDEMM_DOMAIN18_ISR	0.9	-
CDDEMM_DOMAIN19_ISR	0.9	-
CDDEMM_DOMAIN20_ISR	0.9	-
CDDEMM_DOMAIN21_ISR	1.1	-
CDDEMM_DOMAIN22_ISR	1.0	-
CDDEMM_DOMAIN23_ISR	0.9	-
CDDEMM_DOMAIN24_ISR	0.9	-
CDDEMM_DOMAIN25_ISR	0.9	-
CDDEMM_DOMAIN26_ISR	0.9	-
CDDEMM_DOMAIN27_ISR	1.0	-
CDDEMM_DOMAIN28_ISR	0.9	-
CDDEMM_DOMAIN29_ISR	0.9	-
CDDEMM_DOMAIN30_ISR	0.9	-
CDDEMM_DOMAIN31_ISR	0.9	-
CDDEMM_DOMAIN32_ISR	0.9	-
CDDEMM_DOMAIN33_ISR	0.9	-
CDDEMM_DOMAIN34_ISR	0.9	-
CDDEMM_DOMAIN35_ISR	1.1	-
CDDEMM_DOMAIN36_ISR	0.9	-
CDDEMM_DOMAIN38_ISR	0.9	-
CDDEMM_DOMAIN39_ISR	0.9	-
CDDEMM_DOMAIN40_ISR	0.9	-
CDDEMM_DOMAIN41_ISR	0.9	-
CDDEMM_DOMAIN42_ISR	0.9	-

16 CDDICCOM

16.1 CDDICCOM ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_Cddlccom_091.arxml' (DET OFF) and 'RCar_Cddlccom_092.arxml' (DET ON) configuration.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CODE	2212	948
	CODE_FAST	656	656
	CODE_SLOW	3976	3600
	CONFIG_DATA_32	268	268
	Total	7112	5472
RAM	VAR_INIT_32	4	4
	VAR_CLEARED_32	240	240
	VAR_NO_INIT_PTR	8	8
	Total	252	252
	Total	7364	5724

16.2 CDDICCOM Stack Size

This section provides the max of stack depth for the 'RCar_Cddlccom_091.arxml' configuration.

Max of stack depth (Bytes)	480
----------------------------	-----

16.3 CDDICCOM API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_Cddlccom_091.arxml' configuration.

The result is collected with precondition Cortex-R52 L1 Cache OFF.

API Name	Execution time (us)	Remarks
Cddlccom_GetVersionInfo	0.4	-
Cddlccom_Init	1.7	-
Cddlccom_Ch0SendRun	22.4	-
Cddlccom_Ch0ReceiveRun	53.9	-
Cddlccom_MainFunction_Send	7.1	-
MFIS_xlICR0_ISR_RCV_INIT	2.3	-
MFIS_xlICR0_ISR_RCV_ACK	2.3	-
MFIS_xlICR0_ISR_RCV_DATA	3.7	-
MFIS_xlICR0_ISR_RCV_DEINIT	2.3	-

Note: ICCOM driver supports multiple channels, however, the implementation of them are same. Therefore, the test result is collected on Channel 0 for communication between CR52 core 0 and AP-System core (CA76) core 0 domain.

5

17 CDDIIC

17.1 CDDIIC ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_Cddlic_143.arxml(DET ON)' configuration and 'RCar_Cddlic_144.arxml(DET OFF)' configuration.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CODE_ROM	848	848
	CODE_FAST	2396	2396
	CODE_SLOW	5024	4368
	CONFIG_DATA_32	428	428
	Total	8696	8040
RAM	VAR_INIT_1	1	1
	VAR_CLEARED_32	160	160
	VAR_NO_INIT_PTR	8	8
	Total	169	169
Total	-	8865	8209

17.2 CDDIIC Stack Size

This section provides the max of stack depth for the 'RCar_Cddlic_143.arxml' configuration.

Max of stack depth (Bytes)	448
-----------------------------------	-----

17.3 CDDIIC API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_Cddlic_144.arxml' configuration for all API except CDDIIC_DMA_ISR use 'RCar_Cddlic_148.arxml'.

API Name	Execution time (us)	Remarks
Cddlic_Init	31.7	-
Cddlic_GetVersionInfo	0.4	-
Cddlic_ChnSlaveInit (n = 0...5)	5.1	-
Cddlic_ChnWrite (n = 0...5)	8.4	-
Cddlic_ChnRead (n = 0...5)	7.0	-
Cddlic_ChnWriteRead (n = 0...5)	7.2	-
IIC_HW_CHn_ISR (n = 0...5)	1.7	-
CDDIIC_DMA_ISR (n = 0...31)	3.2	-

18 CDDIPMMU

18.1 CDDIPMMU ROM/RAM Usage

This section provides memory usage details measured using the 'RCar_Cddlpmmu_041.arxml (DET ON)' and 'RCar_Cddlpmmu_040.arxml (DET OFF)' configurations.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CODE_SLOW	7996	5412
	CODE_FAST	1048	1048
	CONFIG_DATA_32	24	24
	CONFIG_DATA_UNSPECIFIED	248	248
	Total	9316	6732
RAM	VAR_NO_INIT_PTR	4	4
	VAR_INIT_1	1	1
	Total	5	5
Total	-	9321	6737

18.2 CDDIPMMU Stack Size

This section provides memory usage details measured using the 'RCar_Cddlpmmu_041.arxml (DET ON)' and 'RCar_Cddlpmmu_040.arxml (DET OFF)' configurations.

Max of stack depth (Bytes)	512
-----------------------------------	-----

18.3 CDDIPMMU API Execution Time

This section provides Execution Time details of the API measured using the 'RCar_Cddlpmmu_040.arxml (DET OFF)' configuration.

API Name	Execution time (us)	Remarks
Cddlpmmu_Init	15.6	-
Cddlpmmu_MmuSetMode	0.8	-
Cddlpmmu_MmuSetMemAttr	0.6	-
Cddlpmmu_MmuSetTransTableBase	1.0	-
Cddlpmmu_MmuEnable	0.4	-
Cddlpmmu_MmuDisable	0.4	-
Cddlpmmu_MmuFlush	0.2	-
Cddlpmmu_PmbSet	0.8	-
Cddlpmmu_PmbEnable	0.3	-
Cddlpmmu_PmbDisable	0.3	-
Cddlpmmu_MicroTlbSet	0.8	-
Cddlpmmu_MicroTlbFlush	0.3	-
Cddlpmmu_MmulsEnable	0.1	-
Cddlpmmu_MmuGetMode	0.3	-
Cddlpmmu_MmuGetMemAttr	0.2	-
Cddlpmmu_MmuGetTransTableBase	0.5	-
Cddlpmmu_PmbGet	0.5	-
Cddlpmmu_PmbIsEnable	0.2	-
Cddlpmmu_MicroTlbGet	0.4	-
Cddlpmmu_GetVersionInfo	0.02	-
CDDIPMMU_ERROR_ISR	2.0	-

19 CDDRF50

19.1 CDDRF50 ROM/RAM Usage

This section provides memory usage details measured using the RCar_Cddrfso_011.arxml and RCar_Cddrfso_012.arxml configuration.

ROM/RAM	Section Name	Memory size (Bytes)	
		DET ON	DET OFF
ROM	CONFIG_DATA_32	76	76
	CODE_SLOW	5988	3168
	CODE_FAST	624	624
	Total	6688	3868
RAM	VAR_INIT_1	1	1
	VAR_CLEARED_32	12	12
	VAR_NO_INIT_PTR	4	4
	Total	17	17
Total	-	6705	3885

19.2 CDDRF50 Stack Size

This section provides the max of stack depth for the RCar_Cddrfso_011.arxml and RCar_Cddrfso_012.arxml configuration.

Max of stack depth (Bytes)	384
-----------------------------------	-----

19.3 CDDRF50 API Execution Time

This section provides Execution Time details of the API measured using the RCar_Cddrfso_012.arxml and RCar_Cddrfso_025.arxml configuration.

API Name	Execution time (us)	Remarks
CddRfso_Init	2.6	-
CddRfso_ChannelClockSet	0.6	-
CddRfso_IntervalTimeConfigure	1.5	-
CddRfso_IntervalCycleConfigure	0.4	-
CddRfso_TimeoutTimeConfigure	1.7	-
CddRfso_TimeoutCycleConfigure	0.7	-
CddRfso_StartIntervalTimer	0.2	-
CddRfso_StopIntervalTimer	0.1	-
CddRfso_StartTimeoutTimer	0.1	-
CddRfso_StopTimeoutTimer	0.1	-
CddRfso_ClearTimeoutInterrupt	0.2	-
CddRfso_GetCFEPinStatus	0.2	-
CddRfso_GetTOESPInStatus	0.2	-
CddRfso_ExternalPinControl	0.5	-
CddRfso_GetVersionInfo	0.1	-
CddRfso_GetTimeoutTimerValue	0.2	-
CddRfso_GetIntervalTimerValue	0.2	-
CddRfso_CtrlIntervalTimerInterrupt	0.3	-
CddRfso_IntervalTimerInterruptStatus	0.2	-
CDDRF50_CHANNEL0_ISR	1.0	-
CDDRF50_CHANNEL1_ISR	0.5	-
CDDRF50_CHANNEL2_ISR	0.5	-
CDDRF50_CHANNEL3_ISR	0.5	-
CDDRF50_CHANNEL4_ISR	0.5	-
CDDRF50_CHANNEL5_ISR	0.5	-
CDDRF50_CHANNEL6_ISR	0.5	-
CDDRF50_CHANNEL7_ISR	0.5	-
CDDRF50_CHANNEL8_ISR	0.5	-
CDDRF50_CHANNEL9_ISR	0.5	-
CDDRF50_CHANNEL10_ISR	0.5	-

Revision History		R-Car V4M AUTOSAR R19-11 MCAL Appendix	
Rev.	Date	Description	
		Page	Summary
0.01	Mar.27.24	-	First Edition issued.
0.02	Dec.23.24	-	Update the measurement values for the ICCOM and MCU modules.

R-Car V4M AUTOSAR R19-11 MCAL User's Manual
Appendix

Publication Date: Rev.0.02 Dec.23.24

Published by: Renesas Electronics Corporation

R-Car V4M AUTOSAR R19-11 MCAL
Appendix